# HS-150F Premium Accelerometer

AC acceleration output via M12 Connector

# **Key Features**

· For use with data collector

- Premium design
- Filtered output


#### Industries

Electrical

Case Isolation


Building services, Pulp and Paper, Mining, Metals, Utilities, Automotive, Water, Pharmaceutical







Connection Details



# **Technical Performance**

Mounted Base Resonance	see 'How To Order' table (nominal)
Sensitivity	see: 'How To Order' table ±10%
	Nominal 80Hz at 22°C
Frequency Response	1.5Hz (90cpm) to 10kHz (600kcpm) ± 5%
	0.5Hz (30cpm) to 12kHz (720kcpm) ± 10%
	0.2Hz (12cpm) to 15kHz (900kcpm) ± 3dB
Isolation	Base isolated
Range	see: 'How To Order' table
Transverse Sensitivity	Less than 5%

Mechanical	
Case Material	Stainless Steel
Sensing Element/Construction	PZT/Shear
Mounting Torque	8Nm
Weight	106gms (nominal) body only
Screened Cable Assembly	HS-AC010 - straight
	HS-AC011 - right angle
Mounting Threads	see: 'How To Order' table

18-30Volts DC Excitation Voltage: **Electrical Noise** 0.1mg max **Current Range** 0.5mA to 8mA Bias Voltage 10 - 12 Volts DC Settling Time 2 seconds **Output Impedance** 200 Ohms max.


### Environmental

**Operating Temperature Range** Sealing Maximum Shock EMC

-55 to 150°C IP67 5000 g

EN61326-1:2013

## Typical Frequency Response (at 100mV/g)



#### Applications

Fans, Motors, Pumps, Compressors, Centrifuges, Conveyors, Air Handlers, Gearboxes, Rolls, Dryers, Presses, Cooling, VAC, Spindles, Machine Tooling, Process Equipment

Vibration sensor should be firmly fixed to a flat surface (spot face surface may be needed to be produced and cable anchored to sensor body.)



#### How To Order

>10<sup>8</sup> Ohms at 500 Volts



T: 150 210 98804 www.hansfordsensors.com.cn 汉施弗德传感器(上海)有限公司 CE